

2600.1001

RF modtager 1 kanal fast og hoppende koder

Specifikationer

- **Spænding** : DC12V、DC24V(Jumpervalg)
- **Working temperature**:-40°C-+80°C
- **Frekvens**: 433MHz
- **Antal fjernbetj. :** 30 stykker
- **Størrelse**: 62×43.5×30mm
- **Hvile forbrug**: ≤ 9mA
- **Kontaktsæt** : 10A/48V
- Can identify: Fixed code (2262、2260、2264、5326、M1E、M5E and so on) ,
Learning code (1527、2240、6P20B、6P20D and so on) ,
Rolling code (HCS301、HCS300、HCS200、HCS201、HCS100、HCS101 and so on) ,
Brand remote control (CAME)

II.Output Mode

- A. Signal delayed 9s: short block inserted on 1
- B. Signal latch: short block inserted on 2
- C. Signal momentary: short block inserted on 3
- (Details refer to Wiring diagram)

III.Methods and steps for learning and clearing code

Press "Learning" button on the receiver, release it until LED light flickers, Receiver in learning status (LED goes out this moment), then press related button on Remote control to monitor this Receiver. When LED on Receiver flickers 5 times and then goes out, it indicates Learning has been done. It can response to up to 30 Remote control of this mode.

If Remote control is lost and wanting to make it invalid totally, press "Learning" button (more than 8s) until LED goes out, then Receiver will eliminate all contents automatically. If want to reuse it, just learning one more time again.

IV.Wiring Diagram

